

- 1 -

I hereby certify that this correspondence is being deposited with the United States Postal Service with sufficient postage as Express Mail in an envelope addressed to: BOX PATENT APPLICATION, Assistant Commissioner for Patents, Washington, DC 20231 on:

Date: August 10, 2001

Express Mailing Label No.: ET085698421US

Signature: \_\_\_\_\_

*Crystal Slason*

Typed or Printed Name: Crystal Slason

Inventor(s):

Robert MacArthur

Brian Gallagher

Lawrence Pignolet

Attorney's Docket No.:

EMC01-25(01058)

METHODS AND APPARATUS FOR PROVIDING POWER  
TO ELECTRONIC CIRCUITRY

5

BACKGROUND OF THE INVENTION

A typical computer system includes, among other things, a processor, memory (volatile and non-volatile), and a power supply. The processor runs programs (e.g., an operating system, high-level applications, etc.) which are typically stored in the  
10 memory. The power supply powers circuitry within the processor and the memory.

Some computer systems are configured to perform specialized operations. For example, a typical data storage system is a specialized computer system which is

configured to perform load and store operations on behalf of one or more external hosts. Such a data storage system can include additional or enhanced computer components for performing the load and storage operations. In particular, some of the volatile memory of a data storage system is typically configured to operate as an input/output (I/O) cache  
5 (i.e., cache memory) for temporarily buffering data exchanged between the external hosts and the non-volatile memory (e.g., disk drives).

Some data storage systems include fault tolerant features. For example, one conventional data storage system requires two power supplies to satisfy its entire power needs, but includes three power supplies in the event one of the three power supplies  
10 fails. That is, if one of the three power supplies fails, the remaining two power supplies can continue to provide power so that the data storage system remains operational indefinitely, i.e., so that the data storage system can continue storing and retrieving data on behalf of the external hosts. If one of the remaining two power supplies fails, the data storage system cannot continue operating indefinitely and employs a battery backup  
15 sub-system for a short period of time in order to shutdown safely without losing any data.

The above-described fault tolerant approach to providing power to a computer system using one more power supply than is overall necessary is called using an N+1 redundancy approach. This approach is appropriately named because it uses the number  
20 of power supplies needed to properly power the entire system (N) plus an extra power supply. As such, even if one power supply fails, the system can remain operational.

## SUMMARY OF THE INVENTION

Unfortunately, there are deficiencies to the above-identified conventional  
25 approach to powering a computer system which simply uses N+1 redundancy. For example, the data storage system cannot remain operational indefinitely when more than one power supply fails. Rather, the data storage system must switch to a battery backup sub-system and shutdown in order to avoid losing data. When this occurs, the hosts can no longer store and retrieve data using the data storage system.

In contrast to the above-identified conventional approaches to powering a computer system which simply uses N+1 redundancy, an embodiment of the invention is directed to techniques for powering an electronic system that can distinguish between critical and non-critical circuitry within the system. A first power assembly and a second power assembly provide power to the critical and non-critical circuitry such that a failure of one power assembly results in the remaining power assembly continuing to power the critical circuitry and a portion of the non-critical circuitry in order to continue operation. Each power assembly can include one or more redundant power supplies (e.g., each power assembly having N+1 redundancy) so that, even if an entire power assembly fails and one or more power supplies in the remaining power assembly fails (i.e., even if the system encounters multiple power supply failures), the electronic system can remain operational.

One arrangement of the invention is directed to an electronic system having critical circuitry, non-critical circuitry having a first section and a second section, and a power sub-system. The power sub-system has a first power assembly, a second power assembly, and a set of connections. The set of connections is configured to connect the first and second power assemblies to the critical circuitry and the non-critical circuitry such that, when the first and second power assemblies operate to power the critical and non-critical circuitry through the set of connections, (i) a failure of only the second power assembly results in the first power assembly continuing to power the critical circuitry and the first section of the non-critical circuitry, and (ii) a failure of only the first power assembly results in the second power assembly continuing to power the critical circuitry and the second section of the non-critical circuitry. Accordingly, the system can sustain a failure of an entire power assembly but maintain operation by continuing to power the critical circuitry and a portion of the non-critical circuitry with the remaining power assembly.

In one arrangement, the first section of the non-critical circuitry includes a first set of storage devices, and the second section of the non-critical circuitry includes a second set of storage devices. In this arrangement, the electronic system operates as a

data storage system that stores data into and retrieves data from the first and second sets of storage devices on behalf of a host (e.g., an external computer). The critical circuitry includes cache memory that temporarily buffers data exchanged between the host and the first and second sets of storage devices. Accordingly, a failure of one of the power assemblies still results in the remaining power assembly providing power to the cache memory in order to avoid losing data in the cache memory.

In one arrangement, the second set of storage devices is configured to mirror data on the first set of storage devices. As a result, a failure of one of the power assemblies can result in lost access to one of the sets of storage devices but maintained access to all of the data since the data is mirrored in the other set of storage devices.

In one arrangement, each section of non-critical circuitry includes a front-end interface that operates as an interface between the host and the cache memory, and a first back-end interface that operates as an interface between the cache memory and the first set of storage devices. Accordingly, after a failure of one of the power assemblies, the remaining section of non-critical circuitry (i.e., the section powered by the remaining power assembly) can provide the host with a complete access path to data stored within the storage devices (through the remaining operational front-end interface, cache memory and operational back-end interface).

In one arrangement, the power sub-system includes a first interconnect (e.g., a backplane) that electrically connects to the first set of storage devices, a second interconnect that electrically connects to the second set of storage devices, and a third interconnect that electrically connects to the cache memory, the first front-end and back-end interfaces, and the second front-end and back-end interfaces. The power sub-system further includes a first bus bar assembly that electrically connects the first power assembly to the first and third interconnects, and a second bus bar assembly that electrically connects the second power assembly to the second and third interconnects. Accordingly, both power assemblies have an electrical pathway to the cache memory and to a respective set of storage devices.

In one arrangement, each power assembly includes multiple power supplies (e.g., six power supplies). However, less than all of the multiple power supplies are required to power the critical circuitry and a respective section of the non-critical circuitry (e.g., only four are required). Accordingly, the electronic system can sustain a  
5 failure of all of the power supplies in one power assembly, and at least one power supply on the other assembly (e.g., a failure of two power supplies out of six to leave four which are required) and still remain operational.

In one arrangement, the electronic system further includes a switch which is interconnected between the first and second power assemblies. The switch enables  
10 voltage balancing of the outputs of the first and second power assemblies.

In one arrangement, the electronic system is configured to connect to four different power feeds. In particular, the first power assembly of the power sub-system includes a first set of main power line connectors to connect to a first main power feed, and a first set of auxiliary power line connectors to connect to a first auxiliary power  
15 feed. Similarly, the second power assembly of the power sub-system includes a second set of main power line connectors to connect to a second main power feed, and a second set of auxiliary power line connectors to connect to a second auxiliary power feed. Accordingly, access to multiple power feeds can be lost (e.g., access to three of the power feeds can be lost) but the electronic system can remain operational through the  
20 remaining power feed.

In one arrangement, the first section of the non-critical circuitry further includes a first fan assembly that removes heat from the first section of the non-critical circuitry, and a second fan assembly that removes heat from the second section of the non-critical circuitry. The second section of the non-critical circuitry further includes a third fan  
25 assembly that removes heat from the first section of the non-critical circuitry, and a fourth fan assembly that removes heat from the second section of the non-critical circuitry. Accordingly, both the first and second sections of non-critical circuitry can receive cooling from a fan assembly even if one of the power assemblies becomes unavailable.

In one arrangement, the first section of the non-critical circuitry further includes a first service processor that provides user access and control to the electronic system, and the second section of the non-critical circuitry further includes a second service processor that provides user access and control to the electronic system. Accordingly, a service processor is available to provide a user (e.g., a technician) with access and control to the electronic system even if one of the power assemblies fails.

The features of the invention, as described above, may be employed in computerized systems, devices and methods as well as other electronic components such as those of EMC Corporation of Hopkinton, Massachusetts.

#### BRIEF DESCRIPTION OF THE DRAWINGS

The foregoing and other objects, features and advantages of the invention will be apparent from the following more particular description of preferred embodiments of the invention, as illustrated in the accompanying drawings in which like reference characters refer to the same parts throughout the different views. The drawings are not necessarily to scale, emphasis instead being placed upon illustrating the principles of the invention.

Fig. 1 is a block diagram of an electronic system which is suitable for use by the invention.

Fig. 2 is a block diagram of particular details of the electronic system of Fig. 1.

Fig. 3 is a perspective view of portions of the electronic system of Fig. 1.

Fig. 4 is a block diagram of a cooling sub-system of the electronic system of Fig. 1.

Fig. 5 is a flowchart of a procedure performed by the electronic system of Fig. 1 from a power perspective.

Fig. 6 is the electronic system of Fig. 1 when configured to operate as a data storage system.

## DETAILED DESCRIPTION

An embodiment of the invention is directed to techniques for powering an electronic system having critical and non-critical circuitry. A first power assembly and a second power assembly provide power to the critical and non-critical circuitry such that a failure of one power assembly results in the remaining power assembly continuing to power the critical circuitry and a portion of the non-critical circuitry in order to continue operation. Each power assembly can include one or more redundant power supplies (e.g., each power assembly having N+1 redundancy) so that, even if an entire power assembly fails and one or more power supplies in the remaining power assembly fails (i.e., even if the system encounters multiple power supply failures), the electronic system can remain operational.

Fig. 1 shows an electronic system 20 which is suitable for use by the invention. The electronic system 20 includes critical circuitry 22, non-critical circuitry 24 and a power sub-system 26. The non-critical circuitry 24 includes multiple sections 28-A, 28-B of the non-critical circuitry 24 (collectively, non-critical circuitry sections 28). The power sub-system 26 includes a set of connections 30 and multiple power assemblies 32-A, 32-B (collectively, power assemblies 32). Each power assembly 32-A, 32-B (e.g., an assembly of multiple power supply units) is configured to provide power to the critical circuitry 22 and one of the non-critical circuitry sections 28-A, 28-B through the set of connections 30. For example, the power assembly 32-A is configured to provide power to the critical circuitry 22 and the non-critical circuitry 32-A. Similarly, the power assembly 32-B is configured to provide power to the critical circuitry 22 and the non-critical circuitry 32-B.

The power assemblies 32 are configured such that, when one power assembly 32 fails, the other power assembly 32 can remain operational. Accordingly, when one power assembly 32 fails (e.g., the power assembly 32-A), the other power assembly 32 (e.g., the power assembly 32-B) can continue providing power to the critical circuitry 22 and a section of non-critical circuitry 28 (e.g., the non-critical circuitry section 28-B).

thus enabling the electronic system 20 to remain in operation. Further details of the invention will now be provided with reference to Fig. 2.

Fig. 2 shows particular portions 40 of the electronic system 20. As shown, each power assembly 32-A, 32-B of the power sub-system 26 includes multiple power supply units 42, or simply power supplies. In particular, the power assembly 32-A includes X power supplies 42-A1, ..., 42-AX, and the power assembly 32-B includes Y power supplies 42-B1, ..., 42-BY, where both X and Y are positive integers greater than 1. In one arrangement, each power assembly 32-A, 32-B includes the same number of power supplies 42 (i.e., X equals Y).

10 Additionally, each power assembly 32-A, 32-B includes two sets of power line connectors. In particular, the power assembly 32-A includes a set of main power line connectors 44-A1 for connecting to a main power feed (e.g., a main service leading to a power plant, a generator, etc.), and a set of auxiliary power line connectors 44-A2 for connecting to an auxiliary power feed. Similarly, the power assembly 32-B includes a set of main power line connectors 44-B1 for connecting to a main power feed, and a set of auxiliary power line connectors 44-B2 for connecting to an auxiliary power feed. Preferably, each of the feeds is from a different independent power source so that the power sub-system 26 connects to four independent power sources. As such, each power assembly 32-A, 32-B connects to both a main power source (i.e., the main power feed) and a fallback or redundant power source (i.e., the auxiliary power feed).

Furthermore, the set of connections 30 of the power sub-system 26 includes a set of bus bar assemblies 48-A, 48-B and a set of interconnects 50-A, 50-B, 50-C (e.g., backplanes, cables, adaptors, combinations thereof, etc.) to connect the power assemblies 32-A, 32-B to the critical circuitry 22 and the non-critical circuitry 24. Although only single lines are shown in Fig. 2, it should be understood that the set of connections 30 include multiple conductive paths for carrying current (i.e., a forward path and a return path).

In one arrangement, the power sub-system 30 includes a switch 50 that, when closed, balances the voltage provided by the power assemblies 32-A, 32-B. Preferably,



the power assemblies 32-A, 32-B are shipped pre-configured and adjusted so that little or no current flows through the switch 50. In another arrangement, the power sub-system 30 includes a non-switching connecting member that connects the power assemblies 32-A, 32-B and that operates as if the switch 50 of the earlier-described arrangement is always on. In yet another arrangement, the power assemblies 32-A, 32-B are not connected to each other but precisely matched at the factory so that their voltage outputs are substantially the same.

By way of example only, the electronic system 20 is constructed and arranged as a data storage system. As such, the critical circuitry 22 of the system 20 includes a set of memory modules 54-A, 54-B (e.g., memory circuit boards) which form the cache memory of the data storage system. The non-critical circuitry 24 includes other components such as processors (e.g., directors) and non-volatile storage. In particular, as shown in Fig. 2, the section 28-A of the non-critical circuitry 24 includes a front-end interface 56-A (e.g., a circuit board), a back-end interface 58-A (e.g., another circuit board), a set of storage devices 60-A, a set of fans 62-A and a service processor 64-A. The front-end interface 56-A operates as an interface between one or more external hosts and the cache memory. The back-end interface 58-A operates as an interface between the cache memory and the set of storage devices 60-A. The set of fans 62-A provides air streams that remove heat from the electronic system 20. The service processor 64-A operates as an I/O device (e.g., a console) that provides a user with access to and control of the data storage system.

Similarly, and as further shown in Fig. 2, the section 28-B of the non-critical circuitry 24 includes a front-end interface 56-B (e.g., a circuit board), a back-end interface 58-B (e.g., another circuit board), a set of storage devices 60-B, a set of fans 62-B and a service processor 64-B. The critical circuitry 22 and the components of the non-critical circuitry section 28-B are configured operate as a data storage system in a manner that is similar to the critical circuitry 22 and the non-critical circuitry section 28-A. In particular, the front-end interface 56-B operates as an interface between one or more external hosts and the cache memory. The back-end interface 58-B operates as an

interface between the cache memory and the set of storage devices 60-B. The set of fans 62-B provides air streams that remove heat from the electronic system 20. The service processor 64-B operates as an I/O device (e.g., a console) that provides a user with access to and control of the data storage system.

5       As shown in Fig. 2, each of the interconnects 50-A, 50-B, 50-C includes multiple columns of connectors 66. For example, the interconnect 50-A includes columns of connectors 66 that connect to the storage devices 60-A. Similarly, the interconnect 50-B includes columns of connectors 66 that connect to the storage devices 60-B. The interconnect 50-C includes a column of connectors 66 that connects to the  
10 front-end interface 56-A, a column of connectors 66 that connects to the back-end interface 56-A, columns of connectors 66 that connect to the memory modules 54-A, 54-B, a column of connectors 66 that connects to the front-end interface 56-B, and a column of connectors 66 that connects to the back-end interface 56-B.

As further shown in Fig. 2, the bus bar assemblies 48-A, 48-B connect to the  
15 columns of connectors 66 in order to provide power to the various components (i.e., to the storage devices 60-A, 60-B, front-end interfaces 56-A, 56-B, back-end interfaces 58-A, 58-B, memory modules 54-A, 54-B, etc.). In particular, the bus bar assembly 48-A connects to all of the columns of connectors 66 of the interconnect 46-A in order to carry current between the storage devices 60-A and the power assembly 32-A.  
20 Additionally, the bus bar assembly 48-A connects the columns of connectors 66 of the interconnect 46-C which connect to the front-end interface 56-A, the back-end interface 58-A, and the memory modules 54-A, 54-B in order to carry current between those components and the power assembly 32-A.

Similarly, the bus bar assembly 48-B connects to all of the columns of  
25 connectors 66 of the interconnect 46-B in order to carry current between the storage devices 60-B and the power assembly 32-B. Furthermore, the bus bar assembly 48-B connects the columns of connectors 66 of the interconnect 46-C which connect to the front-end interface 56-B, the back-end interface 58-B, and the memory modules 54-A, 54-B in order to carry current between those components and the power assembly 32-B.

As mentioned earlier, one of the power assemblies 32-A, 32-B can fail and the electronic system 20, which is configured to operate as a data storage system, can remain operational indefinitely. For example, suppose that the power assembly 32-A fails but that the power assembly 32-B does not fail (i.e., continues to provide power).

- 5 The section of non-critical circuitry 28-A, which was powered by that power assembly 32-A, can switch to a battery backup sub-system (not shown) in order to remain in operation for a short period of time to flush out any uncompleted data transfer operations and then shutdown in a controlled, stable and intended manner.

- Concurrently, the power assembly 32-B continues to provide power to the critical  
10 circuitry 22 and the non-critical circuitry section 28-B thus enabling the electronic system 20 to continue to store and retrieve data on behalf on one or more hosts (i.e., thus enabling the system to continue as if nothing failed from the perspective of the hosts). That is, the critical circuitry 22 and the non-critical circuitry section 28-B are configured to operate as a complete data storage system since a complete operating  
15 pathway exists through the front-end interface 56-B, the memory modules 54-A, 54-B, the back-end interface 58-B and the set of storage devices 60-B. Accordingly, the system 20 can continue operation by storing and retrieving data on behalf of one or more external hosts even if the power assembly 32-A becomes unavailable.

- As just mentioned, the critical circuitry 22 and the non-critical circuitry section  
20 28-B are configured to operate as a complete data storage system by storing and retrieving data on behalf of one or more external hosts even when the power assembly 32-A is lost. The remaining section of non-critical circuitry 28-B includes (among other things) an operational front-end interface 56-B, an operational back-end interface 58-B, an operational set of storage devices 60-B thus providing a complete access path  
25 between the external host and non-volatile storage for continued operation. It should be further understood that the set of fans 62-B and the service processor 64-B continue to receive power from the power assembly 32-B and continue to operate as well. Since the critical circuitry 22 and the non-critical circuitry section 28-B continue to receive power

from the remaining power assembly 32-B, no data is lost and no data transfer operations are affected.

Now further suppose that the power supply 42-B1 of the power assembly 32-B fails. Since each of the power assemblies 32-A, 32-B included at least one redundant power supply for fault tolerance (e.g., N+1 redundancy), the power assembly 32-B can continue to provide power to the electronic system 20, and the electronic system 20 can remain in operation.

In one arrangement, the set of storage devices 60-B mirrors data stored in the set of storage devices 60-A. That is, each set of storage devices 60-A, 6-B includes a full copy of the data in the data storage system. Accordingly, a failure of one of the power assemblies 60-A, 60-B results in lost access to only one of the sets of storage devices 60-A, 60-B but maintained access to all of the data since the data is mirrored in the other set of storage devices 60-A, 60-B. In one arrangement, the data storage system continues operation by storing and retrieving data using the remaining set of storage devices 60-A, 60-B. When the failed power assembly 60-A, 60-B is repaired or replaced, the remaining set of storage devices 60-A, 60-B can be synchronized with the lost set of storage devices 60-A, 60-B to restore data mirroring. Further details of the invention will now be provided with reference to Fig. 3.

Fig. 3 shows a perspective view a portion 70 of the electronic system 20. The portion 70 includes a cabinet frame 72 for housing particular circuit components of the electronic system 20. The cabinet frame 72 divides the interior frame cavity into multiple sub-cavities 74-A, 74-B. By way of example only, the power assemblies 32-A, 32-B, the interconnect 46-C, and the circuit boards which connect to the interconnect 46-C (i.e., the interfaces 56-A, 56-B, 58-A, 58-B and the memory modules 54-A, 54-B) reside in the sub-cavity 74-A. The circuit boards and some of the power supplies 42 are omitted from Fig. 3 for simplicity and in order to show other details of the system 20 such as the columns of connectors 66 of the interconnect 46-C.

Also by way of example only, the interconnects 46-A, 46-B and the sets of storage devices 60-A, 60-B which connect to the interconnects 46-A, 46-B reside in the

sub-cavity 74-B. By way of example, the sets of storage devices 60-A, 60-B include disk drive assemblies 82, i.e., a disk drives mounted within disk drive carriers. Some of the storage devices 46-A, 46-B are also omitted from Fig. 3 for simplicity and to show the columns of connectors 66 for connecting to the storage devices 46-A, 46-B. By way of example only, the system 20 further includes additional interconnects 46-D, 46-E for expandability (e.g., for adding non-volatile storage space in the future).

As further shown in Fig. 3, fan assemblies 76-A, 76-B, 76-C, 76-D are formed from the sets of fans 62-A, 62-B (see Fig. 2) and operate as a cooling sub-system for the electronic system 20. The fan assemblies 76-A, 76-B reside at the top of the sub-cavity 74-A. In particular, there are six fans F overall for generating an air stream 80-A therethrough to cool the circuitry housed within the sub-cavity 74-A. Similarly, the fan assembly 76-C, 76-D reside at the top of the sub-cavity 74-B. There are six fans F overall as well for generating an air stream 80-B therethrough to cool the circuitry housed within the sub-cavity 74-B. In one arrangement, sufficient air flow to cool the components within each sub-cavity 74-A, 74-B can be generated by only half the number of fans atop each sub-cavity 74-A, 74-B. That is, only three fans F of the fan assemblies 76-A, 76-B need to run to sufficiently generate the air stream 80-A, and only three fans F of the fan assemblies 76-C, 76-D need to run to sufficiently generate the air stream 80-B.

It should be understood that the frame 72 can include other components in addition to the above-described electronic components. For example, additional electronic components can be housed in the backside 84 of the frame 72. Additionally, wheels 86 can be fastened to the bottom of the frame 72 in order to facilitate moving the frame 72 from one location to another. Further details of the invention will now be provided with reference to Fig. 4.

Fig. 4 shows a portion 100 of the electronic system 20. As shown, a 2x3 array of fans F resides at the sub-cavity top 104-A. The 2x3 array of fans F at the sub-cavity top 104-A is formed by the fan assemblies 76-A, 76-B. The fan assembly 76-A includes fans F-A1, F-A3 and F-A5 of the set of fans 62-A (also see Fig. 2). The fan assembly

76-B includes F-A2, F-A4 and F-A6 of the set of fans 62-B. In one arrangement, the fans F of the fan assemblies 76-A, 76-B are arranged in an interleaved manner as shown in Fig. 4. Since the fans F-A1, F-A3 and F-A5 of the fan assembly 76-A belong to the set of fans 62-A, the fans F-A1, F-A3 and F-A5 are powered by the power assembly 32-A. Similarly, since the fans F-A2, F-A4 and F-A6 of the fan assembly 76-B belong to the set of fans 62-B, the fans F-A2, F-A4 and F-A6 are powered by the power assembly 32-B (see Fig 2).

Similarly, a 2x3 array of fans F resides at the sub-cavity top 104-B. The 2x3 array of fans at the sub-cavity top 104-B is formed by the fan assemblies 76-C, 76-D. The fan assembly 76-C includes fans F-B1, F-B3 and F-B5 of the set of fans 62-A. The fan assembly 76-D includes F-B2, F-B4 and F-B6 of the set of fans 62-B. In one arrangement, the fans F of the fan assemblies 76-C, 76-D are arranged in an interleaved manner (Fig. 4). Since the fans F-B1, F-B3 and F-B5 of the fan assembly 76-C belong to the set of fans 62-A, the fans F-B1, F-B3 and F-B5 are powered by the power assembly 32-A. Similarly, since the fans F-B2, F-B4 and F-B6 of the fan assembly 76-D belong to the set of fans 62-B, the fans F-B2, F-B4 and F-B6 are powered by the power assembly 32-B (see Fig. 2).

If one of the power assemblies 32-A, 32-B fails, some fans F will continue to operate such that a sufficient air stream 80-A, 80-B (Fig. 3) flows through each sub-cavity 104-A, 104-B (as well as the sub-cavities 74-A, 74-B, see Fig. 3) for adequate cooling. For example, suppose that the power assembly 32-B fails, but that the power assembly 32-A continues to provide power. In this situation, the fan assemblies 76-B and 76-D, which were powered by the power assembly 32-B, no longer operate. However, the fan assemblies 76-A and 76-C, which are powered by the power assembly 32-A continue to operate. In particular, the fan assembly 76-A, which includes three fans F-A1, F-A3 and F-A5, continues to generate the air stream 80-A which is sufficient to adequately cool the circuitry within the sub-cavity top 104-A and the sub-cavity 74-A (also see Figs. 2 and 3). Similarly, the fan assembly 76-C, which includes three fans F-B1, F-B3 and F-B5, continues to generate the air stream 80-B which is sufficient to

adequately cool the circuitry within the sub-cavity top 104-B and the sub-cavity 74-B (Figs. 2 and 3). Accordingly, the cooling sub-system 100 continues to properly cool the electronic system 20 even when one of the power assemblies 32-A, 32-B fails. Further details of the invention will now be provided with reference to Fig. 5.

5           Fig. 5 shows a procedure 110 which is performed by the electronic system 20 from a power perspective. In step 112, the electronic system 20 operates the power assemblies 32-A, 32-B to power the critical circuitry 22 and the non-critical circuitry 24. In particular, the power assembly 32-A provides power to the critical circuitry 22 and the first non-critical circuitry section 28-A (also see Fig. 2). Similarly, the power  
10       assembly 32-B provides power to the critical circuitry 22 and the second non-critical circuitry section 28-B.

          In step 114, if there is a power assembly failure, step 114 proceeds to step 116. Otherwise (if there is no failure), step 114 returns to step 112 so that the critical circuitry 22 and both non-critical circuitry sections 28-A, 28-B (i.e., the entire system 20) can  
15       continue operation.

          In step 116, if the first power assembly 32-A failed but the second power assembly 32-B remains in operation, step 116 proceeds to step 118. Otherwise, step 116 proceeds to step 120.

          In step 118, the electronic system 20 performs an error handling procedure for  
20       the first non-critical circuitry section 28-A and continues operating the critical circuitry 20 and the second non-critical circuitry 28-B. For example, the electronic circuitry 22 can switch to a battery backup system for a short period of time so that any partially completed operations of the first non-critical circuitry section 28-A can be completed and so that the first non-critical circuitry section 28-A can be shutdown in a stable and  
25       controlled manner.

          In step 120, if the second power assembly 32-B failed but the first power assembly 32-A remains in operation, step 120 proceeds to step 122. Otherwise, step 118 proceeds to step 124.

In step 122, the electronic system 20 performs an error handling procedure for the second non-critical circuitry section 28-B and continues operating the critical circuitry 22 and the first non-critical circuitry 28-A. For example, the electronic circuitry 20 can switch to a battery backup system so that any partially completed  
5 operations of the second non-critical circuitry section 28-B can be completed and so that the first non-critical circuitry section 28-A can be shutdown in a stable and controlled manner.

Step 124 is performed after any of steps 120 (when both power assemblies 32-A, 32-B failed simultaneously), 118 (when the first power assembly 32-A fails and then  
10 later the second power assembly 32-B fails), 122 (when the second power assembly 32-B fails and then later the first power assembly 32-A fails). In step 124, the electronic system 20 performs an error handling procedure for the circuitry that just lost power. For example, if both power assemblies 32-A, 32-B failed simultaneously (i.e., the electronic system 20 performs steps 114, 116, 118 and 120), the electronic system 20  
15 switches to battery backup so that the critical circuitry 22 and both non-critical circuitry sections 28-A, 28-B are powered to complete any partially performed operations and to shutdown in a stable and controlled manner.

As described above in steps 118 and 122, the electronic system 20 can remain in operation even when one of the power assemblies 32 fails. Further details of the  
20 invention will now be provided with reference to Figs. 2 and 6.

As mentioned earlier in connection with Fig. 2 and by way of example, the electronic system 20 can be constructed and arranged as a data storage system. Fig. 6 shows such a data storage system 132 which is capable of performing load and store operations on behalf of one or more external hosts 134-1, ..., 134-N, e.g., in response to  
25 block I/O signals from the hosts 134-1, ..., 134-N. The front-end interfaces 56-A, 56-B form a front-end 136 of the data storage system 132, the memory modules 54-A, 54-B form a cache memory 138 of the data storage system 132, the back-end interfaces 58-A, 58-B form a back-end 140 of the data storage system 132, and the sets of storage devices 60-A, 60-B (e.g., disk drives) form non-volatile storage 142 of the data storage



system 132 (also see Fig. 2). The front-end 136 operates as an interface between the hosts 134-1, ..., 134-N and the cache memory 138, e.g., transfers blocks of data between the hosts 134-1, ..., 134-N and the cache memory 138. The back-end 140 operates as an interface between the cache memory 138 and the non-volatile storage 142, e.g., transfers blocks of data between the cache memory 138 and the non-volatile storage 142.

As mentioned earlier in connection with Fig. 2, the power sub-system 32 includes multiple power assemblies 32-A, 32-B and preferably connects to four different power feeds. As shown in Fig. 6, the power sub-system 32 of the data storage system 132 connects to four separate power feeds: a first main power feed 144-A and a first auxiliary power feed 146-A which connect to the power assembly 32-A (through the power lines connectors 44-A1, 44-A2, see Fig. 2), and a second main power feed 144-B and a second auxiliary power feed 146-B which connect to the power assembly 32-B (through the power lines connectors 44-B1, 44-B2, see Fig. 2). Accordingly, a failure of the first main power feed 144-A results in the power assembly 32-A continuing to operate through the first auxiliary power feed 146-A. Similarly, a failure of the second main power feed 144-B results in the power assembly 32-B continuing to operate through the second auxiliary power feed 146-B.

A failure of both the main and auxiliary power feeds to a particular power assembly results in the failure of that power assembly. For example, a failure of the first main and auxiliary power feeds 144-A, 146-A results in the failure of the power assembly 32-A. Nevertheless, in such a situation, the other power assembly 32-B continues operation thus maintaining power to the cache memory 142, a front-end interface 56-B, a back-end interface 58-B, a set of storage devices 60-B, etc. (also see Fig. 2). In particular, the other power assembly 32-B can remain in operation using the auxiliary power feed 146-B even when the main power feed 144-B is lost. Accordingly, the data storage system 132 can continue operation even when multiple power feeds are lost.

Additionally, it should be understood that the data storage system 132 can encounter multiple power supply failures and maintain operation. For example, the data storage system 132 can lose all of the power supplies (e.g., X power supplies) in one power assembly 32-A, 32-B (e.g., the power assembly 32-A). Furthermore, the data storage system can lose one or more power supplies in the other power assembly 32-A, 32-B (e.g., the power assembly 32-B) and that power assembly 32-A, 32-B can remain in operation due to built-in redundancy (e.g., N+1 redundancy). Accordingly, the data storage system 132 is more fault tolerant to power-related failures than the earlier described conventional computer system which employs a simple N+1 redundancy approach and fails completely when more than one power supply fails.

As described above, embodiments of the invention are directed to techniques for powering an electronic system 20 having critical 22 and non-critical circuitry 24. A first power assembly 32-A and a second power assembly 32-B provide power to the critical and non-critical circuitry 22, 24 such that a failure of one power assembly (e.g., the power assembly 32-A) results in the remaining power assembly (e.g., the power assembly 32-B) continuing to power the critical circuitry 22 and a portion 28-B of the non-critical circuitry 24 in order to continue operation. Each power assembly 32-A, 32-B can include one or more redundant power supplies 42 (e.g., each power assembly 32-A, 32-B having N+1 redundancy) so that, even if an entire power assembly 32-A, 32-B fails and one or more power supplies 42 in the remaining power assembly 32-A, 32-B fails (i.e., even if the system encounters multiple power supply failures), the electronic system 20 can remain operational. The features of the invention, as described above, may be employed in data storage systems, apparatus and procedures as well as other computer-related components such as those of EMC Corporation of Hopkinton, Massachusetts.

While this invention has been particularly shown and described with references to preferred embodiments thereof, it will be understood by those skilled in the art that various changes in form and details may be made therein without departing from the spirit and scope of the invention as defined by the appended claims.

For example, it should be understood that the electronic system 20 was described above as a data storage system (i.e., a specialized computer system that performs data store and retrieve operations on behalf of hosts) by way of example only. The electronic system 20 can have other configurations and perform other functions as well. For instance, the electronic system 20 can be a general purpose computer, a specialized computer such as a data communications device, a non-processor based apparatus such as a digital logic-designed state machine, a set of application specific integrated circuits (ASICs), a set of field programmable gate arrays (FPGAs), analog circuitry, and/or various combinations thereof. In each of these different configurations, the power system 26 of the electronic system 20 can be arranged so that multiple power assemblies 32-A, 32-B connect to critical circuitry 22 and a respective section 28-A, 28-B of non-critical circuitry 24 so that a failure of a power assembly 32-A, 32-B still enables the remaining power assembly 32-A, 32-B to continue to provide power to the critical circuitry 22 and respective non-critical section 28-A, 28-B of that power assembly 28-A, 28-B for maintained operation of the electronic system 20.

It should be understood that the memory modules 54-A, 54-B were described as being the critical circuitry 22 and other circuits were described as being non-critical circuitry 24 in the above-described data storage system example by way or example only. In other electronic system, different circuitry can reside in the critical circuitry 22 (e.g., processors, controllers, sensors, backup sub-systems, etc.), and different circuitry can reside in the non-critical circuitry 24 (e.g., printers, non-primary sub-systems, etc.).

Additionally, it should be understood that the electronic system 20 was described above as having two power assemblies 32-A, 32-B and two sections 28-A, 28-B of non-critical circuitry 28 by way of example only. Other configurations are suitable as well. For example, the electronic system 20 can have J (e.g., more than two) power assemblies 32 and J non-critical circuitry sections 28. A failure of up to J-1 power assemblies 32 results in at least power assembly 32 remaining in operation to power the critical circuitry 22 and a respective section 28 of non-critical circuitry 24.

Furthermore, it should be understood that the data storage system of Fig. 2 can include more circuit boards than the circuit boards 54-A, 54-B, 56-A, 56-B, 58-A, 58-B shown. For example, the non-critical circuitry section 28-A can include multiple front-end interfaces 56-A and multiple back-end interfaces 58-A for additional throughput and/or redundancy. Similarly, the non-critical circuitry section 28-B can include multiple front-end interfaces 56-B and multiple back-end interfaces 58-B for additional throughput and/or redundancy. Moreover, the critical circuitry 22 can include more memory modules 54-A, 54-B for more buffering of data blocks, redundancy and/or for storing data other than data blocks (e.g., operating system structures, messages exchanged between interfaces, etc.).

Additionally, it should be understood that the data storage system of Fig. 2 was shown as including three interconnects (e.g., backplanes) by way of example only. Other numbers of interconnects are suitable for use as well. For example, as shown in Fig. 3, additional interconnects (e.g., disk drive backplanes) can be added for expandability. Also, backplanes can be coupled together to each other to extend data buses, signal lines, etc. Accordingly, each interconnect can include multiple backplanes which are coupled to each other and which connect to the bus bar assemblies 48-A, 48-B for power.

Furthermore, it should be understood that each power assembly 32-A, 32-B can be configured to provide a single output voltage signal (e.g., +12 VDC), multiple output voltage signals (e.g., +12 VDC, +5 VDC, etc.), direct or alternating currents, etc. For example, in one arrangement, the fans F are powered by an AC output of the power assemblies 32-A, 32-B rather than a DC output. In this arrangement, each of a first fan tray formed by the fan assemblies 76-A, 76-B and a second fan tray formed by the fan assemblies 76-C, 76-D (or alternatively each fan assembly 76-A, 76-B, 76-C, 76-D) preferably includes an AC-DC converting circuit (e.g., two AC-DC converters that step down a 48 Volt output to power a single fan in each tray).

Additionally, it should be understood that the switch 50 is optional. In some arrangements, the switch 50 is omitted or left open in order to assure that a failure on

one half of the electronic system 20 will not take both halves of the electronic system 20 down. In one arrangement, in which the switch 50 is present but left open, the option is then available later to use the switch 50 in a subsequent configuration (e.g., an upgrade) that requires more power than that which is provided by a single power assembly 32-A, 5 32-B. Such modifications and enhancements are intended to be part of embodiments of the invention, and the invention should be limited only by the spirit and scope of the claims.

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000